

## Installation and Maintenance of the LAC02 LEDs

**IMPORTANT:** RETAIN FOR FUTURE REFERENCE. This fixture must be wired and installed in accordance with the NATIONAL ELECTRICAL CODE and all state and applicable local codes and ordinances. These codes and ordinances supersede any and all instruction contained herein. Installation should be performed only by a licensed and bonded electrician and a person familiar with the construction and operation of the product and the hazards involved in the installation and operation of this product. Proper grounding is required for safety. Make certain power is OFF before installing or maintaining fixture. Failure to do so may increase the RISK OF PERSONAL INJURY, PROPERTY DAMAGE, FIRE, AND DEATH. The manufacturer takes no responsibility for the product not installed under those guidelines and those contained in this document. See wiring diagram on back



**Need Help? Call or text us at 216-912-7050**

Power: 120-277V, 50/60Hz

Dimming: 0-10V\* Dimming wires may not be pulled through the fixture depending on how it was ordered.

Lumens: 1500, 1850, or 2400LM - Switch Adjustable.

Kelvins: 30K, 35K, 40K or 50K - Switch Adjustable.

Lens: Comes standard with flat lens with screws, Optionally can be used with a 41 Glass or Lexan Jelly Jar

Guard: Compatible with the 31 Wire Guard or 31 Diecast Guard

Warranty: 5 Years from ship date.

How to adjust lumens and kelvin.

1. If lens, remove with 2 screws or by untwisting.
2. Locate the orange dip switches. Kelvin or Lumen options listed on the side of the switch.
3. Use a flat head screwdriver if needed to adjust the switches.
4. Reinstall the lens or jelly jar.